

X8 Power Source 600



OVERVIEW

Provides 600 A with 40% duty cycle. Control Pad and X8 Cooler always included with the power source.

TECHNICAL SPECIFICATIONS

X8 Power Source 600

| | |
|--|--|
| Product code | X8100601000 (Incl. X8 Control Pad and X8 Cooler) Power upgrade 600 for X8 Power Source - X8560000 |
| Connection voltage 3~ 50/60 Hz | 380 - 460 V ± 10 % 380 - 460 V ± 10 % |
| Fuse | 35 A |
| Open circuit power (MMA) (without cooler and wire feeder, fans OFF) | 44 - 53 W |
| Open circuit power (MMA) (without cooler and wire feeder, fans ON) | 107 - 111 W |
| Open circuit power (MMA) (with cooler, without wire feeder, fans ON) | 132 - 137 W |
| Output 40% ED | 600 A |
| Output 60% ED | 530 A |
| Output 100% ED | 440 A |
| Welding current and voltage range, MIG @ 380 V | 10A/10V - 600A/57V |
| Welding current and voltage range, MMA @ 380 V | 10A/10V - 600A/58,5V |
| Recommended generator power (min) | 40 kVA |
| Open circuit voltage MMA | 50 V |
| Operating temperature range | -20...+40 °C |
| External dimensions LxWxH | 921 x 348 x 795 mm |
| Weight (no accessories) | 95 kg |