

X8 Power Source 400



PANORAMICA

Provides 400 A with a 60% duty cycle. Can be ordered with or without X8 Cooler. Control Pad always included with the power source.

SPECIFICHE TECNICHE

X8 Power Source 400

Codice prodotto	X8100400001 - X8 Power Source 400, CUSTOM (Work Pack + WiseFusion) X8100401000 - X8 Power Source 400, cooler X8100401001 - X8 Power Source 400, cooler, CUSTOM (Work Pack + WiseFusion)
Tensione di collegamento alla rete elettrica 3~ 50/60 Hz	380 - 460 V \pm 10 %
Fusibile	32 A
Potenza a circuito aperto (MMA) (senza unità di raffreddamento e trainafile, ventole OFF)	44 - 53 W
Potenza a circuito aperto (MMA) (senza unità di raffreddamento e trainafile, ventole ON)	107 - 111 W
Potenza a circuito aperto (MMA) (senza unità di raffreddamento, senza trainafile, ventole ON)	132 - 137 W
Erogazione 60% ED	400 A
Erogazione 100% ED	320 A
Intervallo di regolazione corrente e tensione di saldatura, MIG a 380 V	20A/14V - 400A/50V
Intervallo di regolazione corrente e tensione di saldatura, MMA a 380 V	15A/20V - 400A/58V
Potenza del generatore consigliata (min)	25 kVA
Tensione a vuoto (MMA)	50 V
Intervallo temperatura di esercizio	-20...+40 °C
Dimensioni esterne Lu x La x H	921 x 348 x 795 mm
Peso (senza accessori)	95 kg